

Wired ADSL2+ Modem Router

DL4201





Features:

>2 in 1: Combine ADSL2/2+ Modem and Router in a single device

>Provides Quick Start Wizard to help you set up your network in Minutesa

>Slim body design idea for home and office use


>LEDs indicate port activity

Brief:

Create a wired network in your home using the netis DL4201 wired modem Router. Connect this wired router to a broadband modem and share your high-speed Internet access, check email, share files, and enjoy online gaming. With the Quick Start Wizard, you can easily build a wired network and share your high speed internet connection with all the PCs connected to surf the internet, chat online and check mails.

www.netis-systems.com

DL4201



Specification:

1 * 10/100M Auto MDI/MDIX RJ45 1*RJ11
InternetADSL LAN Power
DC 5V/800mA(Output)
72x 69 x 25mm
IEEE 802.3、IEEE 802.3u
Downstream: Up to 24Mbps Upstream: Up to 1Mbps
Full-rate ANSI T1.413 Issue 2 ITU-T G.992.1(G.DMT) ITU-T G.992.2(G.Lite) ITU-T G.992.3 ITU-T G.992.5
ATM Forum UNI3.1/4.0 PVC (up to 8PVCs) ATM Adaptation Layer Type 5 (AAL5) ATM QoS Bridged and routed Ethernet encapsulation VC and LLC based multiplexing PPP over Ethernet (RFC2516) PPP over ATM (RFC 2364) IPoA (RFC1577/2225)
DHCP, DHCP relayNAT, Static RoutingVPN (PPTP, L2TP, IPSec) Pass-throughPVC/Ethernet Port MappingDNS Relay, DDNSIGMP Multicast, IGMP snooping V1/V2Virtual server, DMZ, ACL (Access Control List)UPnP
Web Based Configuration (HTTP), Remote management, Telnet management, command Line Interface, TR-069, SNMP, Web Based Firmware Upgrade, CWMP (TR-069), Diagnostic Tools
CE, FCC
Operating Temperature: $0^{\circ}C \sim 40^{\circ}C$ Storage Temperature: $40^{\circ}C \sim 70^{\circ}C$
Operating Temperature: 0°C~40°CStorage Temperature: -40°C~70°COperating Humidity: 10%~90% non-condensingStorage Humidity: 5%~90% non-condensing

Topological Graph:

