





### N150 Easy-N-Range Extender

TEW-713RE (v1.OR)

TRENDnet's compact N150 Easy-N-Range Extender, model TEW-713RE, extends the coverage of your existing wireless n network. Setup is easy with no drivers to install. Simply press the Wi-Fi Protected Setup (WPS) button on your router or access point, then on the TEW-713RE and you're done—the N150 Easy-N-Range Extender is now extending your wireless N network over a large area.

The compact TEW-713RE conveniently plugs directly into an electrical outlet and the off white housing blends into the environment. An on / off switch is located on the side of the adapter and a LED indicator confirms wireless activity. Hardwire a computer, NAS drive, or printer to the LAN port on the bottom of the extender. The latest wireless encryption protects your network.

#### PRODUCT OVERVIEW

- · Helps eliminate wireless dead spots
- · Compact white housing plugs directly into an electrical outlet
- · Extends the range of your existing wireless network
- · One touch wireless setup using the WPS button
- · Advanced wireless encryption protects your data

#### **FEATURES**

- · Compact wall plug design
- · Compact high performance wireless n range extender
- Data rates of up to 150 Mbps based on IEEE 802.11n
- · Backward compatible with IEEE 802.11b/g devices
- 1 x 10/100 Mbps Ethernet port
- 1 x Wi-Fi Protected Setup (WPS) button
- 1 x Power on / off switch
- · IPv6 support
- Supports up to WPA2-PSK wireless encryption
- One-touch wireless connection using the Wi-Fi Protected Setup (WPS) button
- · Low interference and high susceptibility deliver reliable performance
- · 3-year limited warranty

# N150 Easy-N-Range Extender TEW-713RE (v1.OR)



#### **SPECIFICATIONS**

HARDWARE		
Standards	Based on IEEE 802.11n technology, IEEE 802.11b, IEEE 802.11g     IEEE 802.3u, and IEEE 802.3	
Interface	• 1 x 10/100 Mbps Auto-MDIX LAN port	
LED Indicators	Green     Static: Repeater connect to AP successfully     Flashing: Initializing WPS     Orange     Flashing: Not able to connect to AP     Red     Repeater is restarting	
Power	On / off switch	
Buttons	Reset button: restores factory default settings     WPS button: enables WPS function	
Power Plug	• Input: 100 ~ 240 V, 0.4 A AC, 50~60 Hz	
Dimensions (L x W x H)	• 81 x 52 x 31.5 mm (3.2 x 2.0 x 1.2 in.) – Base • 81 x 52 x 49.5 mm (3.2 x 2.0 x 1.95 in.) – With US plug • 81 x 52 x 70.5 mm (3.2 x 2.0 x 2.78 in.) – With Euro plug (EU)	
Weight	• 79 g (2.8 oz)	
Temperature	• Operating: 0° ~ 40°C (32° ~ 104°F)	
Humidity	Max 90% (non-condensing)	
WIRELESS		
Modulation	OFDM and CCK	
Antenna	Built in antenna	
Frequency	• 2.412 - 2.462 GHz FCC • 2.412 – 2.472 GHz ETSI	
Data Rate (Auto Fallback)	<ul> <li>802.11n: up to 150 Mbps</li> <li>802.11g: up to 54 Mbps</li> <li>802.11b: up to 11 Mbps</li> </ul>	
Output Power	802.11b: 18 dBm (typical) @ 11 Mbps     802.11g: 15 dBm (typical) @ 54 Mbps     802.11n: 14 dBm (typical) @ 150 Mbps	
Receiving Sensitivity	802.11b: -82 dBm (typical) @ 11 Mbps     802.11g: -70 dBm (typical) @ 54 Mbps     802.11n: -70 dBm (typical) @ 150 Mbps	
Encryption	• 64 / 128-bit WEP, WPA / WPA2-PSK	
Channels	• 1-11 (FCC), 1-13 (ETSI)	
Certifications	• CE, FCC	

## N150 Easy-N-Range Extender

TEW-713RE (v1.OR)



#### **NETWORKING SOLUTIONS**



#### PACKAGE CONTENTS

TEW-713RE	
Multi-Language Quick Installation Guide	
CD-ROM (User's Guide)	

#### RELATED PRODUCTS

TEW-712BR	N150 Wireless Router
TEW-731BR	N300 Wireless Home Router
TEW-650AP	N150 Wireless Access Point

#### **CONTACT INFORMATION**

#### TRENDNET<sup>®</sup>

20675 Manhattan Place, Torrance, CA 90501 USA

Tel: 1-310-961-5500 Fax: 1-310-961-5511 Web: www.trendnet.com Email: sales@trendnet.com 1-888-326-6061

