



## Concurrent AC1200 Dual Band WiFi Repeater and Access Point

Easily increase wireless network coverage throughout your home

EM4596

EAN: 8716065331882

Packaging contents: EM4596, QIG, Cat5e cable

### OVERVIEW

- Increase easily your 2.4GHz and 5GHz network coverage
- Crossband technology: get a maximum wireless speed up to 300+900Mbps
- WiFi Signal Indicator: find the best location for the repeater
- Upgrade your network to a Dual Band network
- Four 3dBi antennas for an optimal reach and higher data transfer
- Separated antenna system: use the 2.4GHz and 5GHz band simultaneously
- Easy setup with WPS function
- Installation wizard via your tablet and smartphone
- Also usable as access point
- Two additional 100Mbps LAN ports
- Universally applicable with the most common used wireless routers
- Router function: can be used as a router
- 5-Year warranty
- Accessible helpdesk
- Multilingual user manual
- Easy installation



### SPECIFICATIONS

- Network mode: Repeater, Router and Access Point mode
- Network interface:
  - 1x WAN/LAN 10/100Mbps Ethernet LAN port
  - 1x LAN 10/100Mbps Ethernet LAN port
- Wi-Fi: 300Mbps on 2.4GHz band and 867Mbps on 5GHz band simultaneously
- Complies with IEEE 802.11b/g/n for 2.4GHz band
- Complies with IEEE 802.11ac/a/n for 5GHz band
- Supports WPS: functionality by WPS button
- Security: WEP, WPA and WPA2 wireless security
- Chipset: MT7628A+MT7612E
- Antenna: 4 x 3dbi non detachable external antenna
- Configuration: Webbased
- Dimensions : 50 (W) x 160 (H) x 25 (D) mm
- Weight : 115 g
- Supply voltage range : 100VAC – 240VAC (50/60 Hz)
- Power Consumption : 4W

## Concurrent AC1200 Dual Band WiFi Repeater and Access Point

Easily increase wireless network coverage throughout your home

### DESCRIPTION

**Are you looking for a way to give your WiFi network a boost? Use the EM4596 Concurrent AC1200 Dual Band WiFi Repeater to increase the wireless network coverage for both the 2.4GHz and 5GHz band. Or to upgrade your Single Band network to a Dual Band network. The Crossband technology ensures together with the four 3dBi antennas for the optimum data throughput and network speed: 300+900Mbps. Installing the EM4596 is very easy with the help of the WPS button or installation wizard via your tablet and smartphone. The WiFi signal indicator helps you to find the right location for the repeater.**

#### Dual Band repeater

Does the signal of your wireless network not reach your sofa or garden seat? The EM4596 Concurrent AC1200 Dual Band WiFi Repeater increases the wireless network coverage of your wireless router on the 2.4 GHz and 5GHz band. You will face less interferences when using the 5GHz frequency because it is less crowded and involves hardly any failures.

#### Crossband technology: get highest speed possible

The EM4596 Concurrent Dual Band WiFi Repeater is using the Crossband technology. This technology uses different bands for sending and receiving data packages. For example: the 2.4GHz band is used for the communication between the router and repeater. The communication between the repeater and mobile devices (laptops, tablets and smartphones) is using the 5GHz band. You will get the maximum possible speed!

#### Upgrade your Single Band network to a Dual Band network

Is your 2.4GHz network suffering from many interferences? It is useful to use the 5GHz band. Do you own a Single Band router? We have a solution! The EM4596 Concurrent AC1200 Dual Band WiFi Repeater upgrades your Single Band router to a Dual Band Router. The EM4596 WiFi Repeater receives the 2.4GHz band from your current router and transfers it to both a 2.4GHz and 5GHz output.

#### WiFi signal indicator

Do you find it difficult to find the right location for the repeater? The EM4596 has a special WiFi signal indicator which helps you to find the best location for the repeater. Besides, the four 3dBi antennas ensure an optimal wireless signal and data throughput.

#### Easy setup via WPS button and installation wizard

The EM4596 supports WPS (WiFi Protected Setup). Installing the repeater is very easy. First, press the WPS button on your router. Then, press the WPS button on the Dual Band WiFi Repeater. Do you prefer installing the repeater manually? The installation wizard guides you through the installation process. You can even use your tablet and smartphone. How easy is that?

#### Works with any wireless router

The EM4596 Concurrent WiFi Repeater uses the AC1200 standard, but the repeater is backwards compatible with the 300N standard which is commonly used on all routers. This makes the Concurrent Dual Band WiFi Repeater universally applicable.

#### Usable as access point

The EM4596 WiFi Repeater can function as a Dual Band access point. An access point converts a wired network connection into a wireless signal. You are able to make use of a WiFi signal in places you normally could use a wired connection only.

#### Two additional network ports

The EM4596 can also be used as a wireless bridge for a wired connection of two devices to the network without wiring your home. Additionally, the Concurrent AC1200 Dual Band WiFi Repeater can function as an access point and router too.

## Concurrent AC1200 Dual Band WiFi Repeater and Access Point

Easily increase wireless network coverage throughout your home

### IMAGES



Upgrade your **Single Band** network to a **Dual Band** network



Repeat your **Dual Band** network via **5 GHz**



Repeat your **Dual Band** network via **2.4 GHz**

